

# Fiber Optic Media Converters



- ▶ Utilizes Small Form-factor Pluggable (SFP) modules
- ▶ Multi-mode and single-mode modules available
- ▶ Supports distances up to 20 km (12.4 miles)
- ▶ Surface mount or rack mount capability

The Bosch fiber optic Media Converter series are designed to transmit 10/100 Mbps Ethernet signals over fiber optic cable using Small Form-factor Pluggable (SFP) modules. These fiber optic media converter devices can be used to transmit Ethernet data well beyond the 100 m limit of copper-based media and provides a secure, EMI/RFI free transmission path.

The media converter units are designed to accept 10/100 Mbps SFP modules. The SFP modules are ordered separately to meet user requirements for mode type, distance and type of optical connector. Available offerings include multi-mode fiber (MMF) or single-mode fiber (SMF) models with a single SC connector or dual-fiber with an LC connector.

## System overview

### VG4-SFPSCKT

The VG4-SFPSCKT is a unique media converter module for use with VG4 series AUTODOME cameras incorporating the Ethernet (TCP/IP) Communications Module, as well as with MIC Series 550, 550IR, and 612 cameras and the FLEXIDOME IP starlight 8000i cameras. This media converter module is designed to accept any of the 10/100 Mbps SFP modules described below.

The media converter module along with the SFP module is user installed directly into the power supply box of the AUTODOME camera, FLEXIDOME camera or of the MIC camera to provide an integrated fiber optic solution. Refer to the Installation Guide that accompanies the VG4-SFPSCKT for detailed installation instructions.

### Media converter device (CNFE2MC/IN)

The media converter device (CNFE2MC/IN) is designed to transmit and receive 10/100 Mbps Ethernet data over optical fiber using SFP modules. This head-end device is supplied in an enclosure that can be surface mounted or rack mounted using the optional C1-IN rack mount card cage. The unit does not require in-field adjustments, and provides automatic MDI/MDI-X crossover.

### SFP Modules

The selection of Small Form-factor Pluggable (SFP) modules provides the fast Ethernet optical interface when using the VG4-SFPSCKT or the CNFE2MC/IN media converters. These interchangeable SFP modules are available for use with MMF or SMF optical fiber. The optical fiber SFP modules are available as one and two fiber versions. They also are available with LC or SC optical connectors. The VG4-SFPSCKT and CNFE2MC/IN media converters accept the following SFP modules:

Module	Fiber Type	Optical Interface
SFP-2	MMF	Duplex LC
SFP-3	SMF	Duplex LC
SFP-25	MMF	Single SC
SFP-26	MMF	Single SC

The SFP-25/SFP-26 modules are counterparts; if you use one in the VG4-SFPSCKT module, then you must use the other in the CNFE2MC/IN head-end unit. Refer to the chart below for the acceptable combinations.

If this SFP module is used with the VG4-SFPSCKT	Then this SFP module must be used in the CNFE2MC/IN
SFP-2	SFP-2
SFP-3	SFP-3
SFP-25	SFP-26
SFP-26	SFP-25

### Rack Mount Card Cage (C1-IN)

The rack mount card cage (C1-IN) is designed to hold a maximum of 14 CNFE2MC/IN modules. The C1-IN card cage utilizes an integral, yet field replaceable universal power supply suitable for 120 VAC to 240 VAC, 50/60 Hz operation.

The C1-IN unit includes automatic self-resetting current overload protection, so a fault in any one module will not cause the entire card cage to shut down.

### Closure Panel (C1-BP)

The C1-BP is a closure panel for the C1-IN rack mount card cage, providing coverage for one rack slot.

## Certifications and approvals

Region	Regulatory compliance/quality marks	
Europe	CE	CNFE2MC/IN Media Converter
	CE	VG4-SFPSCKT / FE2MC-B
	CE	SFP

## Installation/configuration notes

The Bosch Fiber Optic Media Converter solution consists of three core components and several optional components to help fit every application. To provide fiber optic communications between a Bosch VG4 AutoDome and a controller, you must use the following:

- One (1) **VG4-SFPSCKT Fiber Optic Ethernet Media Converter Kit** – a printed circuit board installed inside a VG4 power supply box. (See Technical Specification Section 1)
- One (1) **CNFE2MC/IN Ethernet Fiber Optic Media Converter** – a rack-mounted or surface mounted head-end controller. (See Technical Specification Section 2)
- Two (2) **Small Form-factor Pluggable (SFP) modules** – one module is installed in the VG4-SFPSCKT, the other is installed in the CNFE2MC/IN. (See Technical Specification Section 3)

Optionally, you can use the following modules to customize your installation:

- **C1-IN Rack Mount Card Cage** (See Technical Specification Section 4)
- **C1-BP Closure Panel**

To provide fiber optic communications between a MIC Series 550, 550IR, or 612 camera and a controller, you must use the following:

- One (1) **VG4-SFPSCKT Fiber Optic Ethernet Media Converter Kit** – a printed circuit board installed inside a MIC IP power supply box. (See Technical Specification Section 1)
- One (1) **Small Form-factor Pluggable (SFP) module** – one module is installed in the VG4-SFPSCKT. (See Technical Specification Section 3)

## Technical specifications

### Fiber Optic Ethernet Media Converter Kit (VG4-SFPSCKT)

Description	Fiber Optic Ethernet Media Converter kit. Requires a small form-factor pluggable (SFP) module (sold separately).
Data Interface	Ethernet
Data Rate	10/100 Mbps IEEE 802.3 Compliant Full Duplex or Half Duplex Electrical Port Full Duplex Optical Port
Compatible Receiver	CNFE2MC/IN
Installation	Installed inside a NDA-U-PAx, VG4-A-PAx or a VG4-A-PSUx power supply box, or in a MIC IP PSU, with supplied mounting hardware.  Note: Wiring for the VG4-SFPSCKT must be routed through the proper conduit opening on the power supply box. Refer to the installation guide that accompanies the module.

### LED Indicators

Power/Link (on circuit board)	
• Green	Power is applied, fiber link is valid.
• Red	Power is applied, fiber link is missing.
• Green/Flashing Red, rapid	Power is applied. Fiber link is valid. Data is present and video is streaming from the camera to a network connection.

<ul style="list-style-type: none"> <li>Green/Flashing Red, slow</li> </ul>	Power is applied. Fiber link is valid. Data is present. Video is not streaming from the camera, or the RJ45 connection to the camera is not valid.
<b>RJ-45 Connector</b>	
<ul style="list-style-type: none"> <li>Right side, Flashing Green</li> </ul>	Data is present.
<ul style="list-style-type: none"> <li>Right side, Off</li> </ul>	No data is present.
<ul style="list-style-type: none"> <li>Left side, Amber</li> </ul>	Link is valid at 100 MB.
<ul style="list-style-type: none"> <li>Left side, Off</li> </ul>	If the right side is flashing green, link is valid at 10 MB.
<ul style="list-style-type: none"> <li>No LED lit</li> </ul>	The network cable is missing, is defective, or the other end of the network cable is not connected.

**Electrical**

Power	24 VAC @ 220 mA (supplied by the camera)
Current Protection	Automatic resettable Solid-state current limiters
Circuit Board	Meets IPC Standard.

**Mechanical**

Dimensions (LxWxH)	7.4 x 7.1 x 3.8 cm (2.9 x 2.8 x 1.5 in.)
Shipping Weight	0.91 kg (2 lb)

**Environmental**

MTBF	> 100,000 hours
Operating Temperature	-40 °C to +50 °C (-40 °F to +122 °F)

**Ethernet Fiber Optic Media Converter (CNFE2MC/IN)**

Description	Fiber Optic Ethernet Media Converter kit. Requires a small form-factor pluggable (SFP) module (sold separately).
Data Interface	Ethernet
Data Rate	10/100 Mbps IEEE 802.3 Compliant Full Duplex or Half Duplex Electrical Port Full Duplex Optical Port
Installation	Surface mount or rack mount using C1-IN rack (sold separately)

**Connectors**

Power	Terminal block
Electrical	RJ-45 (10/100 BASE-T/TX)
Socket	SFP (10/100 BASE-FX)

**LED Indicators****Link/Act**

<ul style="list-style-type: none"> <li>Green</li> </ul>	Indicates a good fiber connection.
<ul style="list-style-type: none"> <li>Flashing Green</li> </ul>	Indicates data is present on at least one side of the IP connection.
<ul style="list-style-type: none"> <li>No LED lit</li> </ul>	Indicates a loss of fiber connection.

**Power**

<ul style="list-style-type: none"> <li>Green</li> </ul>	Power is supplied.
<ul style="list-style-type: none"> <li>No LED lit</li> </ul>	No power supplied.

**RJ-45 Connector**

<ul style="list-style-type: none"> <li>Right side, Flashing Green</li> </ul>	Data is present.
<ul style="list-style-type: none"> <li>Right side, Off</li> </ul>	No data is present.
<ul style="list-style-type: none"> <li>Left side, Amber</li> </ul>	Link is valid at 100 MB.
<ul style="list-style-type: none"> <li>Left side, Off</li> </ul>	If the right side is flashing green, link is valid at 10 MB.

**Electrical**

Power	
<ul style="list-style-type: none"> <li>Supplied Power Pack</li> </ul>	Input: 90-264 VAC, 50/60 Hz Output: 9 VDC @ 1 A
<ul style="list-style-type: none"> <li>Module:</li> </ul>	8-15 VDC @ 220 mA
Current Protection	Automatic resettable Solid-state current limiters
Circuit Board	Meets IPC Standard.

**Mechanical**

Dimensions (LxWxH)	16.0 x 13.0 x 2.8 cm (6.3 x 5.1 x 1.1 in.)
Shipping Weight	0.91 kg (2 lb)

**Environmental**

MTBF	> 100,000 hours
------	-----------------

Operating Temperature	-40 °C to +75 °C (-40 °F to +167 °F)
Storage Temperature	-40 °C to +85 °C (-40 °F to +185 °F)
Relative Humidity	0% to 95% (non-condensing)
Regulatory Compliance	cUL, UL, RoHS

introduced by connectors, splices, and patch panels. The modules are designed to operate over the entire optical loss budget range, so they do not require a minimum loss in order to operate.

### SFP Modules

Description	Interchangeable modules available for use with MMF or SMF optical fiber.
Data Interface	Ethernet
Data Rate	10/100 Mbps IEEE 802.3 Compliant

### Mechanical

Dimensions (LxWxH)	
• SFP-2, SFP-3	55.5 x 13.5 x 8.5 mm (2.2 x 0.5 x 0.3 in.)
• SFP-25, SFP-26	63.8 x 13.5 x 8.5 mm (2.5 x 0.5 x 0.3 in.)
Weight (all SFP modules)	0.23 kg (0.05 lb)

	Type	Connector	Wavelength (transmit/receive)	Max. Distance
SFP-2	MMF	Duplex LC	1310 nm / 1310 nm	2 km (1.2 miles)
SFP-3	SMF	Duplex LC	1310 nm / 1310 nm	20 km (12.4 miles)
SFP-25	MMF	Single SC	1310 nm / 1550 nm	2 km (1.2 miles)
SFP-26	MMF	Single SC	1550 nm / 1310 nm	2 km (1.2 miles)

### Fiber Compatibility

Optical Fiber Compatibility, MMF	62.5/125 μm MMF. For 50/125 μm fiber, subtract 4 dB from the specified optical budget value. Must meet or exceed fiber standard ITU-T G.651.
Optical Fiber Compatibility, SMF	8–10/125 μm SMF. Must meet or exceed fiber standard ITU-T G.652.
Optical Distance Specifications	Specified transmission distances are limited to the optical loss of the fiber and any additional loss

### Environmental

MTBF	> 100,000 hours
Operating Temperature	-40 °C to +50 °C (-40 °F to +122 °F)

### Rack Mount Card Cage (C1-IN)

Description	Rack mount card cage designed to hold a maximum of 14 CNFE2MC/IN modules
-------------	--

### LED Indicators

<b>Power</b>	
• Red	Power is supplied.
• No LED lit	No power.

### Electrical

Input Voltage	90-264 VAC at 1 A maximum
Output Voltage	9 VDC ± 5% at 6.5 A at +75 °C (+167 °F)
Fusing	1.25 A slow blow (rack power supply) (plug-in modules individually electronically fused)
Power Indicator	Red LED
AC Line Cord	Detachable, IEC-connected. US, European, and UK power cords supplied.

### Mechanical

Dimensions (LxWxH)	48 x 19 x 15 cm (19.0 x 7.5 x 6.0 in.)
Rack Slots	Fourteen (14) 1-in. slots available
Shipping Weight	3.4 kg (7.5 lb)

### Environmental

MTBF	> 100,000 hours
Operating Temperature	-40 °C to +75 °C (-40 °F to +167 °F), ambient
Storage Temperature	-40 °C to +85 °C, (-40 °F to +185 °F), ambient
Heat Generation	240 BTU

Regulatory Compliance	FCC part 15, , cUL, UL, RoHS
-----------------------	------------------------------

### Ordering information

#### VG4-SFPSCKT ETHERNET TO SFP INTERFACE KIT

Ethernet media converter video transmitter/data receiver fiber optic kit for AUTODOME cameras, for MIC-IP-PSU for MIC analog cameras and for the Surveillance cabinets (NDA-U-PA0, NDA-U-PA1 and NDA-U-PA2).

Order number **VG4-SFPSCKT | F.01U.142.529**

#### CNFE2MC/IN Media converter with SFP socket

Single-port 10/100 Mbps Ethernet Media Converter, 120/230 VAC

Order number **CNFE2MC/IN | F.01U.136.545**

#### SFP-2 Fiber module, multimode, 1310nm, 2LC

SFP Fiber Optic Module, 2 km (1.2 miles), 2 LC connectors.

Multi-mode

1310 nm

Order number **SFP-2 | F.01U.136.537**

#### SFP-3 Fiber module, single-mode, 1310nm, 2LC

SFP Fiber Optic Module, 20 km (12.4 miles), 2 LC connectors.

Single-mode

1310 nm

Order number **SFP-3 | F.01U.136.538**

#### SFP-25 Fiber module, 1310/1550nm, 1SC

SFP Fiber Optic Module, 2 km (1.2 miles), 1 SC connector

Multi-mode

1310/1550 nm

Order number **SFP-25 | F.01U.136.541**

#### SFP-26 Fiber module, 1550/1310nm, 1SC

SFP Fiber Optic Module, 2 km (1.2 miles), 1 SC connector

Multi-mode

1550/1310 nm

Order number **SFP-26 | F.01U.136.542**

### Accessories

#### C1-IN Rack mount card cage

EIA 19-in. rack for CNFE2MC, 120-230 VAC

Order number **C1-IN | F.01U.136.543**

#### C1-BP Blank panel for rack mount card cage

Blank panel for C1 rack mount card cage, 1 slot width (1 in.)

Order number **C1-BP | F.01U.136.544**

#### Represented by:

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

##### Germany:

Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Ring 5  
85630 Grasbrunn  
Germany  
www.boschsecurity.com

##### North America:

Bosch Security Systems, LLC  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia